



MC10930B

Long Run Series







Grav LCD



Battery cabinet (Optional)



Optimized battery configuration 7Ah/9Ah (12V)

Features

- High power density
- Online double conversion with full digital control
- Wide input voltage range:110~300Vac
- Input power factor 0.99 with PFC
- Selectable output voltage: 208/220/230/240Vac
- Smart charger design for optimized battery performance
- Maximum charging current can be expanded to 12A (Long run unit)
- Emergency power off function (EPO)
- ECO mode operation for energy saving
- Generator compatible
- Cold start
- Intelligent fan speed regulation
- Load segment settable (Optional)
- Versatile LCD human-computer interface
- Multiple communication interface:RS232 (USB/EPO/Dry contact/SNMP card optional)
- Multiple protection function:short-circuit,overload,overheat, battery overcharge and overdischarge,output low voltage and fan fault alarm





Optional socket



Technical Specifications

3000VA 208/220/230/240Vac 110~300Vac (176~280Vac @ 100% load) 40~70Hz (50/60Hz Auto-Sensing) ≥0.99 208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88% 6 8 9Ah/12V
110~300Vac (176~280Vac @ 100% load) 40~70Hz (50/60Hz Auto-Sensing) ≥0.99 208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave
110~300Vac (176~280Vac @ 100% load) 40~70Hz (50/60Hz Auto-Sensing) ≥0.99 208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave
40~70Hz (50/60Hz Auto-Sensing) ≥0.99 208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave
≥0.99 208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88%
208/220/230/240Vac 0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88%
0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88%
0.9 ±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88%
±1% 46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load ; ≤5% Non linear load 0ms 4ms (Typical) Pure Sinewave 91% 88%
46~54Hz or 56~64Hz (50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load Oms 4ms (Typical) Pure Sinewave 91% 88%
(50/60±0.1%)Hz 3:1 ≤3% Linear load; ≤5% Non linear load Oms 4ms (Typical) Pure Sinewave 91% 88%
3:1 ≤3% Linear load; ≤5% Non linear load Oms 4ms (Typical) Pure Sinewave 91% 88%
3:1 ≤3% Linear load ; ≤5% Non linear load Oms 4ms (Typical) Pure Sinewave 91% 88%
≤3% Linear load ; ≤5% Non linear load Oms 4ms (Typical) Pure Sinewave 91% 88%
Oms 4ms (Typical) Pure Sinewave 91% 88%
4ms (Typical) Pure Sinewave 91% 88% 6 8
Pure Sinewave 91% 88% 6 8
91% 88% 6 8
88%
88%
6 8
'
'
4 hours (to 90% of full capacity)
82.2Vdc±1% 109.6Vdc±1%
62.2VdC±1% 109.0VdC±1%
OA/IZA
.ine mode,Bat.mode,ECO mode,Bypass mode,Battery low voltage,Overload & UPS fault
Input voltage,Input frequency,Output voltage,Output frequency,Load percentage, Battery voltage,Inner temperature& Remaining battery backup time
Dattery Testage, mile temperature a stemaning dattery adeltap time
Beeping every 4 seconds
Beeping every second
Beeping twice every second
Continously beeping
Continues y becoming
191 x 460 x 337
10
10
0°C~40°C
-25°C~55°C
20~95%RH @ 0~40°C (Non condensing)
<1500m,derating required when>1500m
<1500m, derating required when>1500m <50dB at 1 Meter
COUD ALLIVIER
100dB dt 1 Motol
IEC/EN62040-1,IEC/EN62477-1

Specifications are subject to change without prior notice. When output voltage is 208Vac,need to derate to 80% of the unit capacity.